


# Modular Connection Type Residual Pressure Relief 3 Port Solenoid Valve


## VP500/700 Series

For connecting to  
F.R.L. units (AC-A Series)



Allows for space saving  
and reduced piping labor.

Power consumption:  
**0.35 W** (Without light)




### Example of F.R.L. unit connections


#### Simple Specials System

This system enables us to respond to your special needs (additional machining, accessory assembly, or the designing of a modular unit) and deliver your personalized products as quickly as standard products. Please contact your local sales representative for more details.

**VP500**  
AC30C-A + VP500



**VP700**  
AW40-A + VP700



### Modular connection type

VP **5** 1 7   Y - **5** **D**     1 -    

**Series**

5	VP500
7	VP700

**Pressure specification**

Nil	Standard (0.7 MPa)
K	High-pressure type (1.0 MPa)

**Flow direction**

Nil	Left to right
R	Right to left


**Bracket**

Nil	Without bracket
B	With bracket*1

\*1 Brackets are supplied loose, not assembled, at time of shipment. Includes 2 mounting screws.

**Rated voltage**

DC	AC (50/60 Hz)
5 24 VDC	1 100 VAC
6 12 VDC	2 200 VAC
	3 110 VAC [115 VAC]
	4 220 VAC [230 VAC]



### Manual override

Nil: Non-locking push type	A: Non-locking push type (Manual)	E: Push-turn locking type (Manual)

### Light/surge voltage suppressor

	DC	AC
Nil: Without light/surge voltage suppressor	<input type="radio"/>	<input type="radio"/>
S: With surge voltage suppressor	<input type="radio"/>	<input checked="" type="radio"/> *1
Z: With light/surge voltage suppressor	<input type="radio"/>	<input type="radio"/>

\*1 For AC voltage valves there is no "S" option. It is already built into the rectifier circuit.  
\* In the DIN terminal type, since a light is installed in the connector, DOZ and YOZ are not available.

### ⚠ Caution

When using the surge voltage suppressor type, residual voltage will remain. For details, refer to the **Web Catalog** (VP300/500 Low wattage specification).

**Electrical entry**

DIN terminal	DIN (EN175301-803C) terminal


\* Refer to the **Web Catalog** (VP300/500 Low wattage specification) for details of the DIN terminal.

## Simple Specials System

For modular connection units (shipped assembled), the simple specials system can be used. Please contact your local sales representative for more details.

**Products do not come assembled. They should be ordered separately and assembled by the customer.**

## Ordered Separately Example



② AC30-A  
Air filter + Mist separator + Regulator (AF30-A) (AFM30-A) (AR30-A)

\*1 Connection threads are not available for the residual pressure relief 3 port solenoid valve. Order a piping adapter separately.

\*2 Refer to page 1106 for details of the spacer and piping adapter.

- ① Residual pressure relief 3 port solenoid valve VP517Y-5DZ1 ... 1 pc.
- ② Air combination AC30C-03DG ..... 1 pc.
- ③ Spacer with bracket Y300T-A ..... 1 pc.
- ④ Spacer Y300-A ..... 1 pc.
- ⑤ Piping adapter E300-03-A ..... 1 pc.

### Applicable Combinations/Attachment Part Nos.

Residual pressure relief 3 port solenoid valve	Air combination	Spacer	Spacer with bracket	Piping adapter	Silencer
VP517	AC25□-A AC30□-A	Y300-A	Y300T-A	E300-□03-A	AN30-03 AN302-03
VP717	AC40□-A	Y400-A	Y400T-A	E400-□04-A	AN40-04 AN402-04

\* Refer to page 1106 for details of the spacer.

# Modular Connection Type Residual Pressure Relief 3 Port Solenoid Valve *VP500/700 Series*

## Specifications

Fluid		Air
Type of actuation		N.C.
Internal pilot	Standard	0.2 to 0.7
Operating pressure range [MPa]	High-pressure type	0.2 to 1
Ambient and fluid temperature [°C]		-10 to 50 (No freezing)
Maximum operating frequency [Hz]		5
Manual override (Manual operation)		Non-locking push type Push-turn locking type (Manual) Non-locking push type (Manual)
Pilot exhaust method		Individual exhaust
Lubrication		Not required
Mounting orientation		Unrestricted
Impact/Vibration resistance [m/s <sup>2</sup> ]*1		150/30
Enclosure		IP65

\*1 Impact resistance: No malfunction occurred when it was tested in the axial direction and at right angles to the main valve and armature in both energized and de-energized states. Each condition was tested once. (Default settings)  
Vibration resistance: No malfunction occurred in a one-sweep test between 45 and 2000 Hz. Test was performed in both energized and de-energized states in the axial direction and at right angles to the main valve and armature. (Default settings)

## Solenoid Specifications

Electrical entry		DIN terminal (D) DIN terminal (Y) <EN175301-803 (C)>	
		D, Y	
Coil rated voltage [V]	DC	24, 12	
	AC (50/60 Hz)	100, 110, 200, 220	
Allowable voltage fluctuation		±10% of rated voltage*2	
Power consumption [W]	DC	0.35 (With light: 0.45)	
	Standard		
Apparent power [VA]*1	AC	100 V	0.78 (With light: 0.87)
		110 V [115 V]	0.86 (With light: 0.97) [0.94 (With light: 1.07)]
		200 V	1.15 (With light: 1.30)
		220 V [230 V]	1.27 (With light: 1.46) [1.39 (With light: 1.60)]
Surge voltage suppressor		Varistor (DC)	
Indicator light		LED (DC), Neon bulb (AC)	

\*1 The 110 VAC and 115 VAC are interchangeable. The 220 VAC and 230 VAC are interchangeable as well.

\*2 The allowable voltage fluctuation is -15% to +5% of the rated voltage for the 115 VAC or 230 VAC.

## Response Time/Weight



Model	Pressure specifications	Response time [ms](at 0.5 MPa)			Weight [g]
		Without light/surge voltage suppressor	With light/surge voltage suppressor	AC	
VP517Y	Standard (0.2 to 0.7 MPa)	27	32	44	222 (With bracket: 257)
	High-pressure type (0.2 to 1.0 MPa)	41	48	44	
VP717Y	Standard (0.2 to 0.7 MPa)	41	48	50	413 (With bracket: 468)
	High-pressure type (0.2 to 1.0 MPa)	67	76	50	

## Flow Rate Characteristics

Model	Port size EXH.	Flow rate characteristics					
		1→2 (P→A)			2→3 (A→R)		
		C [dm <sup>3</sup> /(s·bar)]	b	Cv	C [dm <sup>3</sup> /(s·bar)]	b	Cv
VP517Y	G3/8	8.8	0.14	2	8.2	0.15	1.8
VP717Y	G1/2	13.8	0.11	2.9	12.9	0.18	2.9



# VP500/700 Series

## Spacer



Model	A	B	C	D
Y300-A	4.2	43.4	21.7	57.9
Y400-A	5.2	53	26.5	68.5

## Spacer with Bracket




Y400T-A

Model	A	B	C	D	E	F	G	H	J	K
Y300T-A	4.2	82	41	71.5	35	14	7	19	4	41
Y400T-A	5.2	96	48	86.1	40	18	9	26	5	50

## Piping Adapter: 3/8, 1/2

A piping adapter allows installation/removal of the component without removing the piping and thus makes maintenance easier.




Model *1	Port size	A	B	D
E300-□03-A	3/8	31.8	30	30
E400-□04-A	1/2	31.8	36	36

\*1 □ in model numbers indicates a pipe thread type. No indication is necessary for Rc; however, indicate N for NPT, and F for G.

\* Separate spacers are required for modular units.


## Silencer

### Compact resin type



Dimensions [mm]			
Model	Port size R	A	B
AN30-03	3/8	58.5	20
AN40-04	1/2	68	24

### High noise reduction type




Model	Port size R	Dimensions [mm]	
		A	B
AN302-03	3/8	84	28
AN402-04	1/2	95	34

# Modular Connection Type Residual Pressure Relief 3 Port Solenoid Valve **VP500/700 Series**


## Dimensions

### VP517





### Details of manual override part (for manual operation)

#### Type A




#### Type E



# VP500/700 Series


## Dimensions

### VP717



### Details of manual override part (for manual operation)

#### Type A



#### Type E

